## QUADRUS<sup>®</sup> EZ



#### Quadrus EZ: At a Glance

- Decodes/second: up to 60
- Read Range: 2 to 10" (51 to 254 mm)
- · Patented Quadrus Technology
- · IP65 Enclosure



ESP® Easy Setup Program: Single-point software provides quick and easy setup and configuration of all Microscan readers.



EZ Trax™: Image capture and storage software provides tracking of symbol images.



EZ Button: This performs reader setup and configuration with no computer required.



Visible Indicators: Performance indicators include "good read" green flash and LEDs, as well as the label positioning tool.

For more information on this product, visit www.quadrus-ez.com.

#### Quadrus EZ: Available Codes

Linear



2D Symbols





Stacked





# Dynamic Smart Camera

The Quadrus EZ smart camera provides an integrated decoding solution for linear, stacked, and 2D symbols. The fully featured Quadrus EZ is exceptionally easy to use and is available in multiple focal distances.

Specializing in dynamic applications, the Quadrus EZ offers accurate decoding of almost any symbol, including direct part marks, with outstanding read rate performance.

#### Ease of Use

Initial set up of the Quadrus EZ can be done in seconds. Position the symbol using the "X" pattern, then push the EZ button to read.

## Field of View Locator & Good Read Flash

A blue "X" identifies the field of view center, allowing fast and accurate symbol placement. The Quadrus EZ emits a bright green flash (visible from all angles) signaling a successful read.

#### Extensive Focal Range

The Quadrus EZ offers four optical versions, factory adjustable from 2 to 10" (50.8 to 254 mm). Adding a camera can expand optical flexibility to increase focal ranges.

#### **Ethernet Connectivity**

Embedded Ethernet is an option available for high speed data and image transfer.

#### **Dynamic Reading**

High decode speeds and superior light collection allow the Quadrus EZ to meet the needs of applications with line speeds up to 600 feet per minute (180 meters/minute).

#### **2D Symbol Quality Reports**

The Quadrus EZ provides printed reports on a variety of quality parameters which are useful in gauging readability of a symbol.

#### Video Input/Output

The Quadrus EZ features video input and output ports. This allows standard analog RS-170 cameras to be used, and a live video feed to view images.

#### **Application Examples**


- Printed circuits assembly
- Automotive
- Aerospace
- · Semiconductor manufacturing



### QUADRUS® EZ DYNAMIC SMART CAMERA

#### SPECIFICATIONS AND OPTIONS

#### **MECHANICAL** Height: 2.25" (57 mm) Width: 2.5" (64 mm) Depth: 4.2" (107 mm) Weight: 12 oz. (340 g)




#### FOUR OPTICAL VERSIONS

Medium Density CCD option shown (right) For more information on Quadrus EZ's other optical versions including Narrow, Wide, and Extra Wide, please contact

#### **MEASUREMENT**

Shown in inches (mm)



## Botton - 1.0" -(25 mm) (19 mm) M4 x .07 .2" deep — (5 mm) nunting holes 4 places 2.97 4.25" (108 mm) Φ .60" (15

## Back .....

#### **ENVIRONMENTAL**

Enclosure: IP65 (standard unit) With Video I/O Option: IP54 Operating Temperature: 0° to 43°C (32° to 109°F), if mounted on a Microscan stand. If mounted on non-metal surface, maximum operating temperature is 40°C (104°F)

Storage Temperature: -50° to 75° C

(-58 to 167°F)

Humidity: up to 90% (non-condensing)

#### **EMISSIONS/IMMUNITY**

ITE Disturbances: EN55022: 1998 (radiated and conducted). Class A

General Immunity: EN55024:1998 (residential) Heavy Industrial Immunity: EN61000-6-2:1999

#### LIGHT SOURCE

Type: High output LEDs

| Г  | WARNING  |
|----|--|
|    | LED LIGHT  |
| D  | O NOT VIEW DIRECTLY WITH OPTICAL INSTRUMENTS     |
|    | CLASS 1M LED PRODUCT                             |
| ı, | Light Output: 648cd Wavelength: 464, 518, 635 nm |
|    | IEC 60825-1:1993+A1:1997+A2:2001                 |

#### **LIGHT COLLECTION OPTIONS**

Progressive scan, square pixel, Software adjustable shutter speed, electronic mechanism CCD Array: 659 x 494 pixels

#### SYMBOLOGY TYPES

2D Symbologies: Data Matrix (ECC 0-200), QR

Code

Stacked Symbologies: PDF417, Micro PDF417, GS1 Databar (Composite & Stacked) Linear Bar Codes: Code 39, Code 128, IBM BC412, I2 of 5, Pharmacode, UPC/EAN

#### STANDARD OFFERING **CONNECTORS/PIN ASSIGNMENTS**

Host Connector: 25-pin D-subminiature plug

| Pin<br>No. | Host<br>RS232                      | Host & Aux<br>RS232 | Host<br>RS422/485 | In/<br>Out |  |
|------------|------------------------------------|---------------------|-------------------|------------|--|
| 1          | Chassis ground <sup>a</sup>        |                     |                   |            |  |
| 2          | TxD                                |                     |                   | Out        |  |
| 3          | RxD                                |                     |                   | In         |  |
| 4          | RTS                                | TxD                 |                   | Out        |  |
| 5          | CTS RxD                            |                     | In                |            |  |
| 6          | Output 1 (+)                       |                     |                   | Out        |  |
| 7          | Signal Ground <sup>b</sup>         |                     |                   |            |  |
| 8          | Output 2 (+)                       |                     |                   | Out        |  |
| 9          | Trigger (–)                        |                     |                   | In         |  |
| 10         | Trigger (+)                        |                     |                   | In         |  |
| 11         | Default configuration <sup>c</sup> |                     |                   | In         |  |
| 12         | Input 1 (+)                        |                     |                   | In         |  |
| 13         |                                    |                     | RxD (+)           | In         |  |
| 14         |                                    |                     | TxD (-)           | Out        |  |
| 15         | Output 3 (+)                       |                     | Out               |            |  |
| 16         |                                    |                     | RxD (-)           | In         |  |
| 17         | Power Ground <sup>d</sup>          |                     |                   |            |  |
| 18         | Power +10 to 28 VDC                |                     | In                |            |  |
| 19         |                                    |                     | TXD +             | Out        |  |
| 20         | Output 1 (–)                       |                     |                   | Out        |  |
| 21         | Output 2 (–)                       |                     |                   | Out        |  |
| 22         | Output 3 (–)                       |                     |                   | Out        |  |
| 23         | Input 1 (–)                        |                     |                   | In         |  |
| 24         | New master (-)                     |                     |                   | In         |  |
| 25         | New master (+) In                  |                     |                   |            |  |

<sup>a</sup>Chassis ground: Used to connect chassis body to earth ground only. Not to be used as power or signal return. Signal ground: Used for communication and signal line grounds only. Not to be used as power or chassis return. <sup>c</sup>The default is activated by connecting pin 11 to ground

d Power ground: Used for power return only. Caution: If using your own power supply, verify correct connection of power and ground lines. Incorrect connections or use of "Chassis ground," "Power ground," and "Signal ground" lines could cause equipment or software failure.

#### **ETHERNET OPTION**

Host Connector: Pins Utilized

| Pin No. | Function         | In/Out |
|---------|------------------|--------|
| 13      | Ethernet RxD (+) | In     |
| 14      | Ethernet RxD(-)  | In     |
| 16      | Ethernet TxD (-) | Out    |
| 19      | Ethernet TxD (+) | Out    |

#### VIDEO INPUT (Option)

Signal System: Progressive scan

Number of Scanning Lines: 525 lines/non-interlaced

#### Input: Analog 1 Vp-p

VIDEO OUTPUT (Option) Signal System: EIA (RS-170)

Number of Scanning Lines: 525 lines/ 2:1 interlaced

Output: Analog 1 Vp-p/75 ohm

#### **READ PARAMETERS**

Pitch: +30° Skew: +30° Tilt: 360° Decode Rate: Up to 60 decodes per second Focal Range: 2 to 10 inches (factory adjustable)

#### **INDICATORS**

LEDS: Read Performance, Power, Read Status, and Net-

work Status

Beeper: Good read, match/mismatch, noread, serial com-

mand confirmation, on/off

#### **COMMUNICATION PROTOCOLS**

Standard Interface: RS-232, RS-422, RS-485

RS-232, Daisy Chain Optional Interface: Ethernet

#### **ELECTRICAL**

Power Requirements: Input, 10 to 28 VDC,

200 mV p-p max ripple, 270 mA at 24 VDC (typ.- CMOS),

333 mA at 24 VDC (typ.-CCD).

Trigger, New Master, Input 1: (Optoisolated) 5 to 28 VDC rated, (12mA at 24 VDC).

Outputs 1/2/3: (Optoisolated) 1 to 28 VDC rated, ( $I_{\text{CE}}$  < 100mA at 24 VDC, current limited by user).

#### SAFETY CERTIFICATIONS

Designed for: FCC, CE, cUL, UL, BSMI





#### **ROHS/WEEE COMPLIANT**

#### ISO CERTIFICATION

Issued by TüV USA Inc, Member of TÜV NORD Group, Cert No. 06-1080

©2008 Microscan Systems, Inc. SP008E 09/08

Read Range and other performance data is determined using high quality Grade A symbols per ISO/IEC 15415 and ISO/IEC 15416 in a 25°C environment. For application-specific Read Range results, testing should be performed with symbols used in the actual application. Microscan Applications tions Engineering is available to assist with evaluations. Results may vary depending on symbol quality.

Warranty-One year limited warranty on parts and labor. Extended

warranty available.

## MICROSCAN

Microscan Systems. Inc.

Tel 425 226 5700 / 800 251 7711

Fax 425 226 8250

Microscan Europe

Tel 31 172 423360 / Fax 31 172 423366

Microscan Asia Pacific R.O.

Tel 65 6846 1214 / Fax 65 6846 4641

Part of a full range of sales tools available from our website

#### www.microscan.com

E-mail: info@microscan.com

Tech Support: helpdesk@microscan.com